

EPS33TDE-KU/LS

Article number: 981113013



Generator :

	<u>3~ 400V</u>	<u>1~ 230V</u>
Output Stand-by (kVA):	33	10.5
Output Stand-by (kW):	26.4	10.5
Output Cont. (kVA):	30	10.5
Output Cont. (kW):	24	10.5
Amps (continuous):	34	46
Dimensions in cm (l x w x h):	209 x 104 x 125	
Dry weight (kg):	1025	

Engine:

Brand / Type:

KUBOTA V3300

Power:	28.9 kW (1500 rpm), Diesel, 4-cylinder, water-cooled
Displacement:	3318 cm ³
Consumption (at full load):	8 litres/hour
Tank:	130 litres
Autonomy (at full load):	17 hours
Starter:	Electric (12V)
Noise level at 75% charge at 7m:	65 dB(A)/7m = Lwa 90
Equipment:	With oil pressure and cooling water temperature security

Alternator:

Brand / Type:

Leroy Somer LSA 42.2L9, 31.5kVA

Nominal voltage:	3~ 400V + 1~ 230V
Frequency:	50 Hz (1500 rpm)

Your EUROPOWER distributor

Arguments:

- Super-silent generating set with KUBOTA V3300 4 cylinder, water-cooled, diesel engine
- Brushless Leroy Somer alternator LSA42.2L9 with AVR (+/- 1% voltage accuracy, with AREP)
- Canopy with 4 lockable doors, external lockable fuel filler cap, central lifting eye
- Chassis with integrated forklift holes, 8 fixation holes, 4 securing eyes, external fuel drain / oil drain / cooling water drain plug
- 4 anti-vibration mounts with interlocking metal protection
- Bunded fuel tank 130 liter, with low fuel level switch, fuel drain plug
- 12V fuel pump and water separator
- The chassis is a bund for cooling water, oil and fuel
- Control panel with:
 - engine control module and starting key
 - low oil pressure and high cooling water temperature shut down with stop solenoid
 - low fuel level and battery voltage alarm
 - voltmeter and selector switch, frequency meter and 3 amp. meters
 - hour-counter and fuel level meter
 - illuminated control panel
 - sockets (2 x schuko 230V, 1 x 16A & 1 x 32A 230V 3 poles CEE, 1 x 32A and 1 x 63A 400V 5 poles CEE)
 - terminals for direct power connection
 - insulation protection "IB Protector" (combined with high voltage, low voltage and high frequency protection, with users code)
 - thermal-magnetic protections
 - emergency stop
 - lockable protection door with window
- Maintenance: fuel filter, oil filter, air cleaner element, oil filler cap, water separator and oil/fuel/cooling water drain at one side
- Battery 12V 100Ah
- 2 gensets can be stacked on top of each other.

Options:

- Earth leakage protection and earth pin (instead of insulation protection)
- Remote control
- Automatic Start Stop System
- Three-way cocks for connection to external fuel tank
- 60 Hz version
-